

## Assembly/operating instructions for SSC-LUXon ZAVO garden socket smart

### 1. Intended use

This product: -can be installed indoors and outdoors -protection type IP44, suitable for use in damp areas  
-must not be exposed to strong mechanical loads or heavy soiling -may not be operated after damp or dirty storage until after a condition check -may not be changed or modified, otherwise the operating permit and conformity will expire with immediate effect! It is not allowed to remove the type plate.

▲ If the aforementioned points are not observed, a short circuit or electric shock may occur! **There is danger to life!**

### 2. General safety instructions

▲ The complete installation may only be carried out by an authorized electrician who is familiar with the applicable guidelines. Hereinafter referred to as „qualified electrician“.  
▲ For safe handling of the product, the user must have read and understood the installation/operating instructions completely before using the device for the first time.  
▲ The product may only be used if it is alright. If the device or parts of it are defective, it must be repaired by a qualified electrician.  
▲ This product is not a toy and is not allowed be stored or used within the reach of children.  
▲ Safe operation of the product is only guaranteed if these instructions are followed. Therefore, keep these assembly/operating instructions. SSC-LUXon GmbH accepts no liability if the instructions given here are not followed or the lamp is subjected to improper use.

### 3. Assembly & configuration

▲ **Caution:** The connecting cable must be disconnected from the power supply before starting work (switch off the main switch/fuse)! Only use parts which are supplied with the product or which are clearly marked as equipment! Otherwise the product may not be sufficiently safe!  
▲ The cable routing shown in the illustrations is for simplified purposes only. They in no way represent a recommendation for connection! The connection may only be carried out by a qualified electrician.  
▲ When drilling, pay attention to cables and gas and water lines. Always route the cable so that it does not touch the light.

#### 3.1 Assembly location

The product is suitable for indoor and outdoor installation. Do not cover the product under any circumstances, especially not with insulating material, fire hazard!

### 4. Operation, faults & disorders

▲ **Caution:** The connecting cable must be disconnected from the power supply before starting work (switch off the main switch/fuse)!

#### What to do in case of error?

In the event of a fault, the unit must be switched off immediately. The product may only be operated if it functions faultlessly. The unit may only be put back into operation after it has been checked by a qualified electrician! **This is the case if:**  
1. there is visible damage, 2. the product is not working correctly, 3. there is smoke, steam, or audible crackling noises, 4. overheating can be detected

▲ **Caution:** There is a danger to life - repairs to the product or work on parts carrying mains voltage may only be carried out by qualified electricians.

#### Avoidance of disturbances and fire hazards:

It is not allowed to cover the product under any circumstances. Air circulation must be ensured. Nothing may be attached or hung on the product, especially no decoration.

### 5. Cleaning & care instructions

The product may only be wiped dry or carefully with a slightly damp and lint-free cloth. The product is not allowed to be removed for this purpose. Do not use abrasive or sharp objects or aggressive cleaning agents. Do not use solvents.

## Assembly instructions ZAVO garden socket smart



1. Do not connect the connecting cable to the mains and disconnect it from the power supply beforehand.
2. Remove the base plate on the lower side by removing the two screws on the side. **Fig.2**
3. Feed the earth cable through the opening and mount the base plate at the desired location using dowels and screws. **Fig.3 & Fig.4**
4. Connect the socket column with the integrated connection box to the mains using e.g. an underground cable. **Fig.5 & Fig.6**
5. Stow the junction box back in the socket column.
6. Reassemble the socket column to the base plate with the previously removed side screws. **Fig.8**
7. The product is now ready for use and the connection line can be released.

▲ **Note:** The power supply can be switched on and off both via app and directly at the socket. There is a switch on the back of the column for this purpose.

▲ **Pairing mode:** To put the power socket in pairing mode, press and hold the button on the socket column for 2-3 seconds.

- Download the smartphone App
- Pairing the socket via WLAN
- Controlling electricity via smartphone

For detailed set-up instructions, simply scan the QR code



[www.led-lichtraum.de/guide/smart](http://www.led-lichtraum.de/guide/smart)

### Short Declaration of Conformity / Frequency Band and Transmitting Power

Hereby, SSC-LUXon GmbH declares that the radio equipment type „Tuya Smart WiFi“ complies with Directive 2014/53/EU.

The full text of the EU Declaration of Conformity can be found at the Internet address [www.led-lichtraum.de/info/doc](http://www.led-lichtraum.de/info/doc).

Frequency band in which the radio system is operated: 2412 - 2483.5 MHz, Max. Transmitting power: +17 dBm.

## Technical data ZAVO garden socket smart



Can be used indoors and outdoors

Type:	Garden socket
Operating temperature:	-20°C - +40°C
Protection type:	IP44
Voltage:	220-240 V / 50-60 Hz
Material:	Stainless steel / plastics
Sockets:	2
Capacity:	16 A / max. 3680 W
Protection class:	I

## Notes, explanations & legend

### Important information



Disconnect the device from the mains power before starting any work



Protection class I



Installation only by qualified electrician



Distance to illuminated objects min. 0.5m



Vers. 02/2023

### Notes on use indoors & outdoors

▲ **Protection type IP20 & IP23:** Use only indoors and dry, i.e. do not use in damp or dirty rooms and in areas of high humidity

▲ **Protection type IP44 & IP65:** Can be used indoors and outdoors



Onlineshop:  
[www.led-lichtraum.de](http://www.led-lichtraum.de)



**Satisfied with your product?**  
Then we look forward to your product review in our online store, on Amazon or eBay!

### Disposal instructions



Make sure to dispose packaging in accordance with the applicable guidelines of your local authority. Devices marked with the crossed-out waste garbage do not belong in the household waste! You are obliged to hand in these devices at one of the free collection points in your municipality. You can obtain more information from your local authority, the relevant town hall or a local or regional waste disposal company.

▲ **Keep packaging material and small parts away from children and animals. Danger of suffocation!**

