

Assembly/operating instructions for SSC-LUXon wall light REVIA

1. Intended use

This product is for lighting purposes only and:

- can be installed indoors and outdoors / protection type IP65,
 - must not be exposed to strong mechanical loads or heavy soiling,
 - may not be operated after damp or dirty storage until after a condition check,
 - may not be changed or modified, otherwise the operating permit and conformity will expire with immediate effect!
- It is not allowed to remove the type plate.

⚠ If the aforementioned points are not observed, a short circuit or electric shock may occur! **There is danger to life!**

2. General safety instructions

- ⚠ The complete installation may only be carried out by an authorized electrician who is familiar with the applicable guidelines. Hereinafter referred to as „qualified electrician“.
- ⚠ For safe handling of the product, the user must have read and understood the installation/operating instructions completely before using the device for the first time.
- ⚠ The product may only be used if it is alright. If the device or parts of it are defective, it must be repaired by a qualified electrician.
- ⚠ This product is not a toy and is not allowed to be stored or used within the reach of children.
- ⚠ Safe operation of the product is only guaranteed if these instructions are followed. Therefore, keep these assembly/operating instructions. SSC-LUXon GmbH accepts no liability if the instructions given here are not followed or the lamp is subjected to improper use.

3. Assembly & configuration

⚠ **Caution:** The connecting cable must be disconnected from the power supply before starting work (switch off the main switch/fuse)! Only use parts which are supplied with the product or which are clearly marked as equipment! Otherwise the product may not be sufficiently safe!

- ⚠ Connection may only be carried out by a qualified electrician.
- ⚠ When drilling, pay attention to cables and gas and water lines.
- ⚠ Always route the cable so that it does not touch the light.

3.1 Assembly location

The product is suitable for indoor and outdoor installation. The product may only be mounted on stable and tilt-resistant walls. Do not cover the product under any circumstances, especially not with insulating material! Fire hazard!

4. Operation, faults & disorders

⚠ Never look directly into the light source!

What to do in case of error?

In case of an error, the device must be switched off immediately. The product may only be operated if it works correctly. The device may only be put back into operation after it has been checked by a qualified electrician! **This is the case if:**

- ⚠ there is visible damage,
- ⚠ the product is not working correctly,
- ⚠ there is smoke, steam, or audible crackling noises,
- ⚠ overheating can be detected.

⚠ **Caution:** There is a danger to life! Repairs to the product or work on parts carrying mains voltage may only be carried out by qualified electricians.

Avoidance of disturbances and fire hazards:

It is not allowed to cover the product under any circumstances. Air circulation must be ensured. Nothing may be attached or hung on the product, especially no decoration.

5. Cleaning & care instructions

The product may only be wiped dry or carefully with a slightly damp and lint-free cloth. The product is not allowed to be removed for this purpose. Do not use abrasive or sharp objects or aggressive cleaning agents. Do not use solvents.

6. Technical data



Can be used indoors and outdoors

Type:	Wall light
Models:	REVIA
Protection type:	IP65
Voltage:	220-240V / 50-60 Hz
Material:	aluminium
Light source:	Fixed/ module
Colour:	Black / golden
Light colour:	Warm white (3000K)
Measurements:	Ø 90 x 300mm height
Note on the energy efficiency class:	This product contains a light source of energy efficiency class F

7. Assembly Instructions



1. **Switch off the fuse!** Switch off the power supply before starting to ensure that no voltage is present.
2. Pull the front part of the light (light body) off the wall bracket. The parts are 'clipped' and can be released by pulling. (Fig. 1)
3. Unscrew the two side screws to separate the wall bracket from the housing. (Fig. 2)
4. Use the wall bracket as a template to mark the drill holes on the wall. Drill the holes and insert the wall plugs.
5. Feed the power cable through the large opening in the wall bracket. Screw the wall bracket firmly to the wall using plugs and screws. (Fig. 3)
6. Connect the cables (L, N and earth if necessary) to the connection terminal. (Fig. 4)
7. Place the light module on the wall bracket and fasten the screws on the side. (Fig. 2 & 5)
8. Clip the light body back onto the mounted module. (Fig. 6)
9. Switch the power supply back on. The light is now ready for operation.

8. General & notes

Important information



Disconnect the device from the mains power before starting any work



Protection class I



Installation only by qualified electrician

Notes on use indoors & outdoors

⚠ **Protection type IP2X:** Use only indoors and dry, i.e. do not use in damp or dirty rooms and in areas of high humidity

⚠ **Protection type IP4X, IP5X & IP6X:** Can be used indoors and outdoors



Onlineshop:
www.led-lichtraum.de



Satisfied with your product?
Then we look forward to your product review in our online store, on Amazon or eBay!



Vers. 06/2024

Disposal instructions



Make sure to dispose packaging in accordance with the applicable guidelines of your local authority. Devices marked with the crossed-out waste garbage do not belong in the household waste!

You are obliged to hand in these devices at one of the free collection points in your municipality. You can obtain more information from your local authority, the relevant town hall or a local or regional waste disposal company.

⚠ **Keep packaging material and small parts away from children and animals. Danger of suffocation!**

