

Assembly/operating instructions for SSC-LUXon recessed floor luminaire MARNE & MADON

1. Intended use

This product is for lighting purposes only and: - can be installed indoors and outdoors - has protection type IP67 - may not be operated after damp or dirty storage until after a condition check - may not be changed or modified, otherwise the operating permit and conformity will expire with immediate effect! It is not allowed to remove the type plate.

▲ If the aforementioned points are not observed, a short circuit or electric shock may occur! **There is danger to life!**

2. General safety instructions

▲ The complete installation may only be carried out by an authorized electrician who is familiar with the applicable guidelines. Hereinafter referred to as „qualified electrician“.

▲ For safe handling of the product, the user must have read and understood the installation/operating instructions completely before using the device for the first time.

▲ The product may only be used if it is alright. If the device or parts of it are defective, it must be repaired by a qualified electrician.

▲ Only use lamps/light sources approved by the manufacturer. The max. lamp wattage in watts is not allowed to be exceeded.

▲ This product is not a toy and is not allowed to be stored or used within the reach of children.

▲ Safe operation of the product is only guaranteed if these instructions are followed. Therefore, keep these assembly/operating instructions. SSC-LUXon GmbH accepts no liability if the instructions given here are not followed or the lamp is subjected to improper use.

3. Assembly & configuration

▲ **Caution:** The connecting cable must be disconnected from the power supply before starting work (switch off the main switch/fuse)! Only use parts which are supplied with the product or which are clearly marked as equipment! Otherwise the product may not be sufficiently safe!

▲ The connection has to be carried out by a qualified electrician only.

▲ When drilling, pay attention to cables and gas and water lines.

▲ Always route the cable so that it does not touch the luminaire.

▲ Components of the luminaire and especially the lamps/light sources become hot during operation. Especially in the case of halogen lamps/light sources. Keep a sufficient distance (0.5 m) from easily flammable objects (e.g. curtains, drapes, etc.) and flammable materials (ignition temperature < 250°C)!

4. Operation, bulb replacement, faults & disorders

▲ **Caution:** Disconnect the connecting cable from the power supply before replacing lamps/light sources!

Halogen lamps/lamps become very hot during operation - risk of burns! Therefore, do not touch the protective glass or the reflector! Allow to cool down before replacing! Do not cover! There is a risk of fire when covering (e.g. with towel)! Lamps with protective cover may only be operated with complete protective cover!

▲ Never look directly into the light source!

What to do in case of error?

In case of an error, the device must be switched off immediately. The product may only be operated if it works correctly. The device may only be put back into operation after it has been checked by a qualified electrician! This is the case if:

1. there is visible damage
2. the product is not working correctly
3. there is smoke, steam, or audible crackling noises
4. overheating can be detected

▲ **Caution:** There is a danger to life - repairs to the product or work on parts carrying mains voltage may only be carried out by qualified electricians.

Avoidance of disturbances and fire hazards:

It is not allowed to cover the product under any circumstances. Air circulation must be ensured. Nothing may be attached or hung on the product, especially no decoration.

5. Cleaning & care instructions

The product may only be wiped dry or carefully with a slightly damp and lint-free cloth. The product is not allowed to be removed for this purpose. Do not use abrasive or sharp objects or aggressive cleaning agents. Do not use solvents.

Technical data model MARNE



Can be used indoors and outdoors

Type:	Recessed floor luminaire round
Model:	MARNE
Protection type:	IP67
Voltage:	230V / 50-60Hz
Material:	Die-cast aluminium / glas / stainless steel
Light source:	GU10 (max. 35W)
Cutout:	Ø 95mm without built-in box / Ø 102mm with built-in box
Measurements:	Ø 108mm
Installation depth:	150mm (incl. light source and built-in box)
Loadable up to:	max. 2000Kg
Cable gland:	M22x1,5 - cable diameter 10-14 mm

Technical data model MADON



Can be used indoors and outdoors

Type:	Recessed floor luminaire square
Model:	MADON
Protection type:	IP67
Voltage:	230V / 50-60Hz
Material:	Die-cast aluminium / glas / stainless steel
Light source:	GU10 (max. 35W)
Cutout:	Ø 95mm without built-in box / Ø 102mm with built-in box
Measurements:	120 x 120mm
Installation depth:	145mm (incl. light source and built-in box)
Loadable up to:	max. 2000Kg
Cable gland:	M22x1,5 - cable diameter 10-14 mm

6. Assembly instructions

1. Disconnect the connecting cable from the power supply.
2. Measure and cut out the cutout (Ø see technical data).
3. Loosen the screws on the front - Detach the inner part from the front.
4. Remove the glass pane and the sealing ring from the inner part.
5. Loosen the screws from the plate inside on which the luster terminal is fixed.
6. Pull the plate forward to access the luster terminal.
7. Unscrew the cable glands (PG) on the underside.
8. Guide the cable glands (PG) over your connection line.
9. Guide the connection cable through the holes into the inside of the inner part.
10. Connect the connecting cable with the luster terminal.
11. Screw the cable glands (PG) back onto the inner part.
12. Reattach the plate with the luster terminal in the inner part.
13. Place the bulb in the socket provided.
14. Place the inner part in the cut-out hole.
15. Replace the sealing ring as well as the glass pane.
16. Mount the stainless steel plate incl. glass pane with the smooth side facing upwards on the enclosure.
17. The product is now ready for use.

7. General & notes



Disconnect the device from the mains power before starting any work



Protection class I



Installation only by qualified electrician



Online store:
www.led-lichtraum.de



Satisfied with your product?
Then we look forward to your product review in our online store, on Amazon or eBay!



Make sure to dispose packaging in accordance with the applicable guidelines of your local authority. Devices marked with the crossed-out waste garbage do not belong in the household waste! You are obliged to hand in these devices at one of the free collection points in your municipality. You can obtain more information from your local authority, the relevant town hall or a local or regional waste disposal company.

▲ **Keep packaging material and small parts away from children and animals. Danger of suffocation!**